



999.00 EUR incl. 19% VAT, plus <u>shipping</u>

- Intel Rapid BIOS Boot
- DDR-II RAM
- 1.2Ghz CPU
- SATA !

Note : Mainboard is like Intel D201GLY2, but with fan !

The Intel® Desktop Board D201GLY2A is an innovative solution for the sub-value market segment. With an Intel® Celeron® processor and graphics integrated on the board, this board enables easy system integration and helps you to achieve a lower system cost. This board has 10/100 LAN, support up to six Hi-Speed USB 2.0 ports and 2 SATA (1.5 GB/s), providing both connectivity and ease of use for your computing needs such as email and Internet access, instant messaging and Voice Over IP (VoIP).

The Intel Desktop Board D201GLY2A is built in smaller uATX-Compatible form factor providing lower power consumption and passive



thermal solution.

Form Factor	uATX (6.75 inches by 6.75 inches [171.45 millimeters by 171.45
	millimeters]) (ITX compatible)
Processor	Integrated Intel® Celeron® 220 processor (1.2 Ghz) with a 533
	MHz system bus
Memory	One 240-pin DDR2 SDRAM Dual Inline Memory Module (DIMM)
	sockets
	Support for DDR2 677/533/400 MHz DIMMs
	Support for up to 1 GB of system memory
Chipset	SiS* SiS662 Northbridge
	SiS* SiS964L Southbridge
Audio	ADI* AD1888 audio codec
Video	Integrated SiS Mirage* 1 graphic engine
I/O Control	Winbond* W83627DHG-B based Legacy I/O controller for
	hardware management, serial, parallel, and PS/2* ports
LAN Support	10/100 Mbits/sec LAN subsystem using the Broadcom* LAN
	adapter device
Peripheral Interfaces	Six USB 2.0 ports
	One parallel ATA IDE interface with UDMA 33, ATA-66/100/133
	support
	Two SATA ports
	One serial port
	One parallel port
	PS/2* keyboard and mouse ports
Expansion Capabilities	One PCI Conventional* bus connector

Note : The CPU heatsink has a height of 45mm. Thats why it does not fit into every enclosure.

Compatible with :

- Voom

- Voom-2

- M300(-LCD)

- Travla C137

Not compatible with :

- M200(-LCD) (needs replacement heatsink)

- Morex enclosures (needs replacement heatsink)

PicoPSU & M3-ATX: You can only directly stick in the standard picoPSU-120 power supply. Other picoPSU models and M3-ATX can only be connected with an additional ATX extension cable.

For Operating you need a P4 adapter or a PSU with P4 connector